


THL 20WI Resistor Trim Table (single output only)



THL 20-xx10WI

Trim down	1	2	3	4	5	6	7	8	9	10	%
Vout =	3.276	3.234	3.201	3.168	3.135	3.102	3.069	3.036	3.003	2.970	Volt
Rd =	63.59	30.28	18.19	11.95	8.13	5.56	3.70	2.31	1.21	0.34	KOhms
Trim up	1	2	3	4	5	6	7	8	9	10	%
Vout =	3.333	3.366	3.399	3.432	3.465	3.498	3.531	3.564	3.597	3.630	Volt
Ru =	70.50	29.28	16.87	10.90	7.38	5.06	3.42	2.20	1.25	0.49	KOhms

THL 20-xx11WI

Trim down	1	2	3	4	5	6	7	8	9	10	%
Vout =	4.950	4.900	4.850	4.800	4.750	4.700	4.650	4.600	4.550	4.500	Volt
Rd =	45.53	20.61	12.31	8.15	5.66	4.00	2.81	1.92	1.23	0.68	KOhms
Trim up	1	2	3	4	5	6	7	8	9	10	%
Vout =	5.050	5.100	5.150	5.200	5.250	5.300	5.350	5.400	5.450	5.500	Volt
Ru =	36.57	16.58	9.92	6.59	4.59	3.25	2.30	1.59	1.03	0.59	KOhms

THL 20-xx12WI

Trim down	1	2	3	4	5	6	7	8	9	10	%
Vout =	11.880	11.760	11.640	11.520	11.400	11.280	11.160	11.040	10.920	10.800	Volt
Rd =	394.50	179.74	106.08	68.86	46.39	31.36	20.60	12.51	6.21	1.17	KOhms
Trim up	1	2	3	4	5	6	7	8	9	10	%
Vout =	12.120	12.240	12.360	12.480	12.600	12.720	12.840	12.960	13.080	13.200	Volt
Ru =	368.92	161.92	94.97	61.86	42.12	29.00	19.66	12.66	7.23	2.89	KOhms

THL 20-xx13WI

Trim down	1	2	3	4	5	6	7	8	9	10	%
Vout =	14.850	14.700	14.550	14.400	14.250	14.100	13.950	13.800	13.650	13.500	Volt
Rd =	572.67	248.63	145.60	94.97	64.87	44.92	30.72	20.10	11.86	5.28	KOhms
Trim up	1	2	3	4	5	6	7	8	9	10	%
Vout =	15.150	15.300	15.450	15.600	15.750	15.900	16.050	16.200	16.350	16.500	Volt
Ru =	392.98	182.12	108.73	71.43	48.85	33.71	22.86	14.69	8.33	3.23	KOhms

THL 20-xx15WI

Trim down	1	2	3	4	5	6	7	8	9	10	%
Vout =	23.760	23.520	23.280	23.040	22.800	22.560	22.320	22.080	21.840	21.600	Volt
Rd =	598.89	267.94	157.63	102.47	69.38	47.31	31.56	19.74	10.54	3.19	KOhms
Trim up	1	2	3	4	5	6	7	8	9	10	%
Vout =	24.240	24.480	24.720	24.960	25.200	25.440	25.680	25.920	26.160	26.400	Volt
Ru =	487.11	218.06	128.37	83.53	56.62	38.69	25.87	16.26	8.79	2.81	KOhms